

## Axis product selection result



Camera	AXIS M5014	AXIS P5534-E	AXIS P5544	AXIS Q6034-E	AXIS Q6035-E
<b>Camera</b>					
Image sensor	CMOS	CCD	CCD	CCD	CMOS
Image sensor size	1/4"	1/3"	1/3"	1/3"	1/2.8"
Megapixel sensor	✓	✓	✓	✓	✓
Sensor size in megapixel	1	1.3	1.3	1.3	2
Progressive scan	✓	✓	✓	✓	✓
Wide dynamic range		✓	✓	✓	✓
Min illumination/ light sensitivity (Color)	1.4 lux	0.74 lux	0.74 lux	0.74 lux	0.8 lux
Min illumination/ light sensitivity (B/W)		0.04 lux	0.04 lux	0.04 lux	0.04 lux
<b>Video</b>					
Day and Night functionality		✓	✓	✓	✓
Max video resolution	1280x720	1280x720	1280x720	1280x720	1920x1080
Max frames per second	30	30/25	30/25	30/25	60/50
<b>Lens</b>					
Focal length	3.6 mm	4.7 - 84.6 mm	4.7 - 84.6 mm	4.7 - 84.6 mm	4.7 - 94 mm
Varifocal					
Aperture	1.8	1.6	1.6	1.6	1.6
Horizontal field of view	60	55.2 - 3.2	55.2 - 3.2	55.2 - 3.2	54.1 - 2.9
Lens mount					
Lens changeable					
<b>PTZ</b>					
Mech. Pan/Tilt	✓	✓	✓	✓	✓
Digital Pan/Tilt					
Pan range	+/-180	+/-180	+/-180	+/-180 endless	+/-180 endless
Tilt range	90	180	180	220	220
Guard tour		✓	✓	✓	✓
Optical zoom		18	18	18	20
Digital zoom	3	12	12	12	12
<b>Compression</b>					
Motion JPEG	✓	✓	✓	✓	✓
MPEG-4					
H.264	✓	✓	✓	✓	✓
HDTV resolution	720p	720p	720p	720p	1080p
<b>Audio</b>					
Audio support	✓		✓*		
Two-way audio			✓*		
Full duplex audio			✓*		
Built-in microphone	✓				

Built-in speaker					
<b>System Integration</b>					
Video motion detection	✓	✓	✓*	✓	✓
Audio detection	✓		✓		
Active tampering					
Alarm inputs/outputs	0/0	0/0	4*	0/0	0/0
Serial connectors					
AVHS	✓	✓	✓	✓	✓
<b>Network</b>					
QoS	✓	✓	✓	✓	✓
IPv6	✓	✓	✓	✓	✓
Power over Ethernet	✓	✓	✓	✓	✓
PoE class	3	HI POE	HI POE	HI POE	HI POE
Wireless					
<b>Security</b>					
Multi-level password	✓	✓	✓	✓	✓
HTTPS encryption	✓	✓	✓	✓	✓
IP address filtering	✓	✓	✓	✓	✓
IEEE 802.1X	✓	✓	✓	✓	✓
<b>General</b>					
Slot for memory card	✓	✓	✓	✓	✓
Operational temperature °C	0 to 45	-20 to 50	0 to 50	-40 to 50	-40 to 50
Vandal resistant					
IP rating	IP51	IP66	IP51	IP66	IP66
Comments	* -	* -	* Audio, I/O and/or power in requires multicable sold as accessory, configurable alarm inputs/outputs	* -	* -